## 1-1 True Finder での IP アドレス変更

付属の CD に有る True Finder を起動します。

☑ TrueFinder.exe をダブルクリックします。

🚨 True	Finder	_	_	_	_	_	_0×
Dev	rice Gelect all devices						Found 0 devices
	IP address	MAC address	Base port	HTTP port	IP mode	Model name	Firmware



le Help						
	(P)					
Device Select all device						Equal 4 danies
Device Select all device	ns				_	Found 4 device
Device Delect all device IP address	MAC address	Base port	HTTP port	IP mode	Model name	Found 4 device
Device Select all device IP address 192.168.0.35	MAC address	Base port 2235	HTTP port 8035	IP mode Fixed IP	Model name IPTZ-200M	Found 4 device Firmware V1.504803-T100
Device Delect all device IP address 192.168.0.35 192.168.0.40	MAC address 00:1C 00:1C	Base port 2235 2240	HTTP port 8035 8040	IP mode Fixed IP Fixed IP	Model name IPTZ-200M LAN-HD264	Found 4 device Firmware V1.504803-T100 V1.504803-T100
Device Delect all device IP address 192.168.0.35 192.168.0.40 192.168.0.70	MAC address 00:1C 00:1C 00:1C	Base port 2235 2240 2270	HTTP port 8035 8040 8070	IP mode Fixed IP Fixed IP Fixed IP	Model name IPTZ-200M LAN-HD264 LAN-HD264D	Found 4 device Firmware V1.504803-T100 V1.504803-T100 V4.605R01_T100
Device IP address 192.168.0.35 192.168.0.40 192.168.0.70 192.168.0.70	MAC address 00:1C 00:1C 00:1C 00:1C	Base port 2235 2240 2270 2273	HTTP port 8035 8040 8070 8073	IP mode Fixed IP Fixed IP Fixed IP Fixed IP	Model name IPTZ-200M LAN-H0264 LAN-H0264E LAN-H0264ED	Found 4 device Firmware V1.504803-T100 V1.504803-T100 V4.605R01_T100 V4.511R01_T100

── IP アドレスを変更する機器の☑にチェックを入れます。

変更する行を選択します。

**が**をクリックします。

設定変更窓が開きますので変更項目を指定して Chang ボタンを押す。

変更後のボタンを押すとブラウザが開きます。

🔍 IP change	×
IP mode	Fixed IP V
IP Address	192 . 168 . 10 . 100
Subnet mask	255 . 255 . 255 . 0
Gateway	192 . 168 . 10 . 1
Base port	2222 (1025~65535)
Http port	80 (80, 1025~65535)
	Change Close